

Pin-Out Table

Termination Board field side			Modules			Termination Board control side	
Module	Channel	IS terminals M1 ... M16	IS terminals SL2 field side	Non-IS terminals SL1 control side	Non-IS terminals M1 ... M16	Signal name	
1	1	1	5a	8a	11	CH1+	
		4	5b	7a	14	CH1-	
	2	2	1a	10a	12	CH2+	
		5	1b	9a	15	CH2-	
2	3	1	5a	8a	11	CH3+	
		4	5b	7a	14	CH3-	
	4	2	1a	10a	12	CH4+	
		5	1b	9a	15	CH4-	
3	5	1	5a	8a	11	CH5+	
		4	5b	7a	14	CH5-	
	6	2	1a	10a	12	CH6+	
		5	1b	9a	15	CH6-	
4	7	1	5a	8a	11	CH7+	
		4	5b	7a	14	CH7-	
	8	2	1a	10a	12	CH8+	
		5	1b	9a	15	CH8-	
5	9	1	5a	8a	11	CH9+	
		4	5b	7a	14	CH9-	
	10	2	1a	10a	12	CH10+	
		5	1b	9a	15	CH10-	
6	11	1	5a	8a	11	CH11+	
		4	5b	7a	14	CH11-	
	12	2	1a	10a	12	CH12+	
		5	1b	9a	15	CH12-	
7	13	1	5a	8a	11	CH13+	
		4	5b	7a	14	CH13-	
	14	2	1a	10a	12	CH14+	
		5	1b	9a	15	CH14-	
8	15	1	5a	8a	11	CH15+	
		4	5b	7a	14	CH15-	
	16	2	1a	10a	12	CH16+	
		5	1b	9a	15	CH16-	
9	17	1	5a	8a	11	CH17+	
		4	5b	7a	14	CH17-	
	18	2	1a	10a	12	CH18+	
		5	1b	9a	15	CH18-	
10	19	1	5a	8a	11	CH19+	
		4	5b	7a	14	CH19-	
	20	2	1a	10a	12	CH20+	
		5	1b	9a	15	CH20-	
11	21	1	5a	8a	11	CH21+	
		4	5b	7a	14	CH21-	
	22	2	1a	10a	12	CH22+	
		5	1b	9a	15	CH22-	
12	23	1	5a	8a	11	CH23+	
		4	5b	7a	14	CH23-	
	24	2	1a	10a	12	CH24+	
		5	1b	9a	15	CH24-	

Pin-Out Table

Termination Board field side			Modules		Termination Board control side	
Module	Channel	IS terminals M1 ... M16	IS terminals SL2 field side	Non-IS terminals SL1 control side	Non-IS terminals M1 ... M16	Signal name
13	25	1	5a	8a	11	CH25+
		4	5b	7a	14	CH25-
	26	2	1a	10a	12	CH26+
		5	1b	9a	15	CH26-
14	27	1	5a	8a	11	CH27+
		4	5b	7a	14	CH27-
	28	2	1a	10a	12	CH28+
		5	1b	9a	15	CH28-
15	29	1	5a	8a	11	CH29+
		4	5b	7a	14	CH29-
	30	2	1a	10a	12	CH30+
		5	1b	9a	15	CH30-
16	31	1	5a	8a	11	CH31+
		4	5b	7a	14	CH31-
	32	2	1a	10a	12	CH32+
		5	1b	9a	15	CH32-

Terminal pin-out	Connector	Pin	Channel
HART Signal	HART1	1, 2	CH1+, CH1-
		3, 4	CH2+, CH2-
		5, 6	CH3+, CH3-
		7, 8	CH4+, CH4-
		9, 10	CH5+, CH5-
		11, 12	CH6+, CH6-
		13, 14	CH7+, CH7-
		15, 16	CH8+, CH8-
		17, 18	CH9+, CH9-
		19, 20	CH10+, CH10-
		21, 22	CH11+, CH11-
		23, 24	CH12+, CH12-
		25, 26	CH13+, CH13-
		27, 28	CH14+, CH14-
		29, 30	CH15+, CH15-
		31, 32	CH16+, CH16-
	HART2	1, 2	CH17+, CH17-
		3, 4	CH18+, CH18-
		5, 6	CH19+, CH19-
		7, 8	CH20+, CH20-
		9, 10	CH21+, CH21-
		11, 12	CH22+, CH22-
		13, 14	CH23+, CH23-
		15, 16	CH24+, CH24-
		17, 18	CH25+, CH25-
		19, 20	CH26+, CH26-
		21, 22	CH27+, CH27-
		23, 24	CH28+, CH28-
		25, 26	CH29+, CH29-
		27, 28	CH30+, CH30-
		29, 30	CH31+, CH31-
		31, 32	CH32+, CH32-

TDOCT-3638_ENG 260436 03/2014


Refer to "General Notes Relating to Pepperl+Fuchs Product Information".

Pepperl+Fuchs Group
www.pepperl-fuchs.comUSA: +1 330 486 0002
pa-info@us.pepperl-fuchs.comGermany: +49 621 776 2222
pa-info@de.pepperl-fuchs.comSingapore: +65 6779 9091
pa-info@sg.pepperl-fuchs.com

Pin-Out Table

Terminal pin-out	Connector	Pin	Signal name
Power supply	X20	6	Supply I -
		5	Supply I +
	X20	4	Supply II -
		3	Supply II +
Fault	X20	1, 2	Fault

Module pin-out (SL1): module 1 ... 16	
V _{cc}	2a (+)
	2b (+)
GND	1a (-)
	1b (-)
Fault	6b

 The loop drawing has to be observed. For information see corresponding data sheet on www.pepperl-fuchs.com.