

inductance per unit length L': 0.4 ... 1 mH/km

Separately powered equipment needs a galvanic isolation to assure that

The cable used to interconnect the devices needs to have the parameters in

15 ... 150 Ohm /km

One of the allowed terminations might already be integrated in the associated apparatus.

C'= C' line/line + 0.5 C' line/screen, if both lines are floating or C'= C' line/line + C' line/screen,

At each end of the trunk cable an approved infallible line termination with the following parameters is suitable:

length of trunk cable: 1 km length of splice: 1 m

the intrinsically safe fieldbus circuit remains passive.

capacitance per unit length C': 80 ... 200 nF/km

if the screen is connected to one line

 $R = 90 \dots 100 \text{ Ohm}$ $C = 0 \dots 2.2 \text{ uF}$.

length of spur cable: 30 m

the following range: loop resistance R´:

NONHAZARDOUS LOCATION

Any
FM Approved
Associated
Apparatus
Suitable for
Entity-concept
or
FISCO-concept

Intrinsically safe installations intrinsically safe for Cl. I,II,III Div.1, Gp. ABCDEFG;

AEx ia IIC T6

- 1. FM Approved apparatus must be installed in accordance with manufacturer instructions
- 2. FM Approved associated apparatus must meet the following requirements:

 Uo or Voc or Vt ≤ Ui (Vmax) and Io or Isc or It ≤ Ii (Imax) and Po or Pmax ≤ Pi (Pmax)
- 3. The maximum non-hazardous area voltage must not exceed 250 V.
- 4. The installation must be in accordance with the National Electrical Code NFPA 70 (NEC) and ANSI/ISA RP 12.06.01 (except chapter 5).
- 5. Be aware of multiple earthing of screen. The screen must be connected in accordance with National Electrical Code.
- 6. Caution: Use only supply wires suitable for 5 °C above surrounding temperature
- 7. Warning: Substitution of components may impair intrinsic safety.
- 8. The polarity for connecting PA+ (1) and PA- (2) is of no importance due to an internal rectifier.

Division 2 and Zone 2 installation

Nonincendive Class I, Div.2, group A,B,C,D Hazardous Location Installation (not for separated housing)

- 9. Installation shall be in accordance with NEC using threaded conduits or other wiring methods in accordance with articles 500 to 510.
- Intrinsic safety barrier not required. Max. supply voltage 32 V. For T-code see table.
- 10. Warning: Explosion Hazard- Do not disconnect equipment unless power has been switched off or the area is known to be non hazardous
- 11. Nonincendive field wiring installation
- The Nonincendive Field Wiring Circuit Concept allows interconnection of nonincendive field wiring apparatus with associated nonincendive field wiring apparatus or associated apparatus not specifically examined in combination as a system using any of the wiring methods permitted for unclassified locations, when Vmax \leq Voc or Vt, Ca \leq Ci + Ccable, La \leq Li + Lcable Transmitter parameters are as follows: Vmax = 32 VDC; Ci \leq 5 nF; Li \leq 10 µH; Imax = see note 12
- 12. For these current controlled circuit, the parameter Imax is not required and need not to be aligned with parameter Isc and It of the nonincendive field wiring or associated apparatus. Warning: Substitution of Components may impair suitability for Class I, Div.2
- 13. The transmitter is suitable to be installed according the FISCO (former FNICO) concept.

Class II. III installation

DIP for Class II and III, Div.1, group E, F, G Hazardous Location Installation (not for separated housing)

14. Installation of transmitter wiring according to NEC using threaded conduits or other wiring methods in accordance with articles 500 to 510.

FM Control Drawing no. 116-0398

Dieses Dokument enthält sicherheitsrelevante Angaben. Es darf nicht ohne Absprache mit dem Normenfachmann (NE Ex) geändert werden!

This document contains safety-relevant information. It must not be altered without the authorization of the norm expert (NE Ex)!

CONFIDENTIAL acc. to ISO 16016

Only valid as long as released in EDM or with a valid production documentation!

Control Drawing - FM

PPC-M51, LHC-M51 Profibus PA

sheet 4 of 4