

1 **EU - TYPE EXAMINATION CERTIFICATE**

2 **Safety Device, Controlling Device or Regulating Device intended for use outside a potentially explosive atmosphere but required for or contributing to the safe functioning of Equipment and Protective Systems with respect to the risks of explosion**
Directive 2014/34/EU

3 EU - Type Examination Certificate Number: **Baseefa06ATEX0092 – Issue 3**

3.1 In accordance with Article 41 of Directive 2014/34/EU, EC-Type Examination Certificates referring to 94/9/EC that were in existence prior to the date of application of 2014/34/EU (20 April 2016) may be referenced as if they were issued in accordance with Directive 2014/34/EU. Supplementary Certificates to such EC-Type Examination Certificates, and new issues of such certificates, may continue to bear the original certificate number issued prior to 20 April 2016.

4 Product: **Type KCD2-SR-Ex*. * Switch Amplifier**

5 Manufacturer: **Pepperl + Fuchs GmbH**

6 Address: **Lilienthalstrasse 200, 68307 Mannheim, Germany**

7 This re-issued certificate extends EC Type Examination Certificate No. Baseefa06ATEX0092 to apply to product designed and constructed in accordance with the specification set out in the Schedule of the said certificate but having any variations specified in the Schedule attached to this certificate and the documents therein referred to.

8 SGS Baseefa, Notified Body number 1180, in accordance with Article 17 of Directive 2014/34/EU of the European Parliament and of the Council, dated 26 February 2014, certifies that this product has been found to comply with the Essential Health and Safety Requirements relating to the design and construction of products intended for use in potentially explosive atmospheres given in Annex II to the Directive.

The examination and test results are recorded in confidential Report No. **See Certificate History**

9 Compliance with the Essential Health and Safety Requirements has been assured by compliance with:

EN 60079-0:2012+A11:2013 EN 60079-11:2012

except in respect of those requirements listed at item 18 of the Schedule.

10 If the sign “X” is placed after the certificate number, it indicates that the product is subject to the Specific Conditions of Use specified in the schedule to this certificate.

11 This EU - TYPE EXAMINATION CERTIFICATE relates only to the design and construction of the specified product. Further requirements of the Directive apply to the manufacturing process and supply of this product. These are not covered by this certificate.

12 The marking of the product shall include the following :

Ex II (1) GD [Ex ia Ga] IIC (-20°C ≤ Ta ≤ +60°C)

[Ex ia Da] IIIC (-20°C ≤ Ta ≤ +60°C)

Ex 1 (M1) [Ex ia Ma] I (-20°C ≤ Ta ≤ +60°C)

SGS Baseefa Customer Reference No. **0808**

Project File No. **17/0873**

This document is issued by the Company subject to its General Conditions for Certification Services accessible at <http://www.sgs.com/en/Terms-and-Conditions.aspx> and the Supplementary Terms and Conditions accessible at <http://www.sgs.com/SGSBaseefa/Terms-and-Conditions.aspx>. Attention is drawn to the limitation of liability, indemnification and jurisdiction issues defined therein. Any holder of this document is advised that information contained herein reflects the Company's findings at the time of its intervention only and within the limits of Client's instructions, if any. It does not necessarily indicate that the equipment may be used in particular industries or circumstances. The Company's sole responsibility is to its Client and this document does not exonerate parties to a transaction from exercising all their rights and obligations under the transaction documents. This document cannot be reproduced except in full, schedule included, without prior written approval of the Company. Any unauthorized alteration, forgery or falsification of the content or appearance of this document is unlawful and offenders may be prosecuted to the fullest extent of the law.

SGS Baseefa Limited

Rockhead Business Park, Staden Lane,
Buxton, Derbyshire SK17 9RZ

Telephone +44 (0) 1298 766600 Fax +44 (0) 1298 766601

e-mail baseefa@sgs.com web site www.sgs.co.uk/baseefa

Registered in England No. 4305578.

Registered address: Rossmore Business Park, Ellesmere Port, Cheshire, CH65 3EN



R S SINCLAIR
TECHNICAL MANAGER
On behalf of SGS Baseefa Limited

13

Schedule

14

Certificate Number Baseefa06ATEX0092

15 Description of Product

The Type KCD2-SR-Ex*. Switch Amplifiers are designed to transfer digital signals from the hazardous area to unspecified apparatus located in the non-hazardous area. The voltage and current passed to the hazardous area are limited to intrinsically safe levels and have linear characteristics. Up to two hazardous area channels fitted are galvanically isolated from the non-hazardous area circuit using transformers.

The Type KCD2-SR-Ex*. Switch Amplifier comprise a number of electronic components, including isolating transformers, fuses, zener diodes and resistors all mounted on a single printed circuit board and housed in a plastic enclosure with polarised plug-in screw or spring (denoted with an ".SP" suffix) terminals for hazardous and non-hazardous area connections. The non-hazardous area connections are via relay contacts with configuration switches allowing the setting of the direction of operation and lead monitoring. LED indication is provided for power-on and channel status.

There are three models of the Type KCD2-SR-Ex*. Switch Amplifier, the Type KCD2-SR-Ex2(.SP) Two Channel Switch Amplifier, the Type KCD2-SR-Ex1(.SP) Single Channel Amplifier and Type KCD2-SR-Ex1.LB(.SP) Single Channel Switch Amplifier. The Types KCD2-SR-Ex1(.SP) & KCD2-SR-Ex1.LB(.SP) are depopulated versions of the Type KCD2-SR-Ex2(.SP) with only one hazardous area channel.

Input/Output Parameters

Non-Hazardous Area Terminals 5 to 8, 9 & 10 and Power Rail Connections PR1 & PR2

$$U_m = 253V \text{ r.m.s.}$$

The circuit connected to non-hazardous area terminals 9 & 10 or Power Rail Connections PR1 & PR2 is designed to operate from a d.c. supply voltage up to 30V.

Non-hazardous area terminals 5 & 6 (Channel 1) and 7 & 8 (Channel 2) are connected to relay contacts which can switch up to 253V r.m.s & 2A r.m.s.

Power Rail Connections PR4 (Fault Bus)

$$U_m = 40V \text{ d.c.}$$

The circuit connected to Power Rail Connection PR4 is designed to operate from a d.c. supply voltage up to 30V.

Hazardous Area Terminals 1 w.r.t. 2 (Channel 1)

or

Hazardous Area Terminals 3 w.r.t. 4 (Channel 2 – KCD2-SR-Ex2 model only)

$$\begin{aligned} U_o &= 10.5V & U_i &= 12V \\ I_o &= 17.1mA \\ P_o &= 45mW \\ C_i &= 0 \\ L_i &= 0 \end{aligned}$$

The capacitance and either the inductance or inductance to resistance ratio (L/R) of the load connected to output terminals of either channel must not exceed the following values:

GROUP	CAPACITANCE (μ F)	INDUCTANCE (mH)	OR L/R RATIO (μ H/ Ω)
IIC	2.41	121.5	801
IIB/IIIC	16.8	486.3	1,628
IIA	75.0	972.7	1,628
I	73.1	1,000	1,628

The above parameters apply when one of the two conditions below is given:

- the total L_i of the external circuit (excluding the cable) is $< 1\%$ of the L_o value or
- the total C_i of the external circuit (excluding the cable) is $< 1\%$ of the C_o value.

The above parameters are reduced to 50% when both of the two conditions below are given:

- the total L_i of the external circuit (excluding the cable) $\geq 1\%$ of the L_o value and
- the total C_i of the external circuit (excluding the cable) $\geq 1\%$ of the C_o value.

Note: the reduced capacitance of the external circuit (including cable) shall not be greater than 1 μ F for Groups I, IIA & IIB/IIIC and 600nF for Group IIC.

16 Report Number

See Certificate History

17 Specific Conditions of Use

None.

18 Essential Health and Safety Requirements

In addition to the Essential Health and Safety Requirements (EHSRs) covered by the standards listed at item 9, the following are considered relevant to this product, and conformity is demonstrated in the report:

Clause	Subject	Compliance
1.2.7	LVD type requirements	Manufacturer responsibility
1.2.8	Overloading of equipment (protection relays, etc.)	User/Installer responsibility
1.4.1	External effects	User/Installer responsibility
1.4.2	Aggressive substances, etc.	User/Installer responsibility

19 Drawings and Documents

New drawings submitted for this issue of certificate:

None.

Current drawings which remain unaffected by this issue:

Number	Sheet	Issue	Date	Description
16-533BS B	1 of 1	B	2011-Oct-25	Summary – KCD2-SR-Ex*.*
16-533BS-00A	1 to 8	A	2006-Nov-15	Description – KCD2-SR-Ex*.*
16-533BS-01	1 & 2	-	2006-Apr-25	Schematic – KCD2-SR-Ex2 K-System Slimline
16-533BS-01	3 & 4	-	2006-Apr-25	Schematic – KCD2-SR-Ex1.* K-System Slimline
16-533BS-02	1	-	2005-Dec-05	Relevant Components – KCD2-SR-Ex*.* / HiC282*
16-533BS-03	1 of 5	-	2005-Sep-30	Assembly drawing wired top side – KCD2-SR-Ex1.* / KCD2-SR-Ex2
16-533BS-03	2 of 5	-	2005-Sep-30	Assembly drawing SMD top side – KCD2-SR-Ex2
16-533BS-03	3 of 5	-	2005-Sep-30	Assembly drawing SMD bottom side – KCD2-SR-Ex2
16-533BS-03	4 of 5	-	2005-Sep-30	Assembly Drawing SMD top side – KCD2-SR-Ex1.*
16-533BS-03	5 of 5	-	2005-Sep-30	Assembly Drawing SMD bottom side – KCD2-SR-Ex1.*

Number	Sheet	Issue	Date	Description
16-533-04	1 & 2	-	2005-Dec-05	Housing – KCD2
16-533BS-05	1 to 4	-	2005-Sep-30	PCB Layout – KCD2-SR-Ex1 (-Ex2)(LB)
16-533BS-06A	1 to 4	A	2006-Nov-15	Transformer – KCD2-SR-Ex*.* / HiC282*
16-533BS-09	1 & 2	-	2006-Apr-25	Instructions – KCD2-SR-Ex*.*
16-533BS-10B	1 & 2	B	2011-Oct-25	Type Label – KCD2-SR-Ex*.*

The above drawings are associated and held with IECEx Certificate No. IECEx BAS 06.0025

20 Certificate History

Certificate No.	Date	Comments
Baseefa06ATEX0092	1 June 2006	The release of the prime certificate. The associated test and assessment against the requirements of EN 60079-0:2004, EN 50020:2002, EN 60079-26:2004, IEC 61241-0:2004 & EN 61241-11:2005 is documented in Test Report No. 05(C)0856/1. Project File No. 05/0856.
Baseefa06ATEX0092/1	29 November 2006	To permit minor transformer design changes. Project File No. 06/0971.
Baseefa06ATEX0092/2	1 March 2012	To permit the use of spring terminal plugs, these units are identified with a “.SP” suffix, and to additionally confirm that the equipment meets the requirements of EN 60079-0:2009 & EN 60079-11:2007. Report No. GB/BAS/ExTR12.0043/00. Project File No. 11/0857.
Baseefa06ATEX0092 Issue 3	14 March 2018	This issue of the certificate incorporates previously issued primary & supplementary certificates into one certificate and confirms the current design meets the requirements of EN 60079-0:2012+A11:2013 & EN 60079-11:2012. The equipment description has had minor changes and Group IIIC has also been added to the load parameter tables. Report No. GB/BAS/ExTR18.0047/00. Project File No. 17/0873.
For drawings applicable to each issue, see original of that issue.		