ANZEx

Australian/New Zealand Certification Scheme
for Explosion Protected Equipment

Certificate of Conformity

Ex EQUIPMENT

Certificate No.: **ANZEx 13.2004X**	*Current Issue:* 3	*Date of Issue:* 2026-06-08

Applicant: **Pepperl+Fuchs SE**
Lilienthalstrasse 200
68307 Mannheim
GERMANY

Equipment: KFD2-STC(V)4-Ex1(.2O)… Smart Transmitter Isolator

Type of Explosion Protection: Intrinsic Safety 'i'

Explosion Protection Marking: [Ex ia Ma] I
-20 °C ≤ Ta ≤ +60 °C

This certificate is granted subject to the requirements as set out in
Joint Accreditation System of Australia and New Zealand Publications
ANZEx System Rules 2020 & ANZEx Certified Equipment Scheme Rules 2021

Signed for and on behalf of issuing body .....

Name & Position *Geoff Barnier*
Principal Engineer - Certification
.....

This certificate is not transferable and remains the property of the issuing body.
The status of this certificate can be confirmed through the database located at www.anzex.com.au

Certificate issued by:

Safety in Mines, Testing and Research Station
2 Robert Smith Street, REDBANK QLD 4301

JAS-ANZ
WWW.JAS-ANZ.ORG/REGISTER

This certificate and schedule may only be reproduced in full

Simtars

Certificate of Conformity
Ex EQUIPMENT

Certificate No.: **ANZEx 13.2004X**	*Current Issue:* 3	*Date of Issue:* 2026-06-08

Manufacturer :
Pepperl+Fuchs SE
Lilienthalstrasse 200
68307 Mannheim
GERMANY

Manufacturing Location(s):
Pepperl+Fuchs Asia Pte. Ltd.
18 Ayer Rajah Crescent
Singapore 139942
SINGAPORE

Pepperl+Fuchs (Vietnam) Co. Ltd.
Lot S.12-16a, Street no. 20
Tan Thuan Export Processing Zone
Tan Thuan Ward
Ho Chi Minh City
VIETNAM

STANDARDS:

The equipment and any acceptable variations to it specified in the schedule of this certificate and the identified documents, was found to comply with the following standards:

IEC 60079-0: 2011 Ed 6.0	Explosive atmospheres Part 0: Equipment – General requirements
IEC 60079-11: 2011 Ed 6.0	Explosive atmospheres Part 11: Equipment protection by intrinsic safety “i”

This Certificate does not indicate compliance with safety and performance requirements other than those expressly included in the Standards listed above.

This certificate and schedule may only be reproduced in full

Certificate of Conformity
Ex EQUIPMENT

Certificate No.:	ANZEx 13.2004X	Current Issue: 3	Date of Issue: 2026-06-08

Schedule

Equipment Description:

The KFD2-STC(V)4-Ex1(.2O)... Smart Transmitter Isolator is designed to provide galvanic isolation between intrinsically safe circuits in a hazardous area and circuits in a safe area and limit voltage and current into the hazardous area to intrinsically safe levels.

The apparatus comprises a number of electrical components, including transformers, fuses, resistors and zener diodes, all mounted on a single printed circuit board and housed within a plastic enclosure fitted with terminals for external connections.

The use of 'C' or 'V' in the type description specifies Current source / sink or Voltage respectively.

Options following 'Ex1' in the type description are:

.2O (Dual non-hazardous area output)

-Y… (Current sink - used with 'C')

-1 (5 Volt - used with 'V')

-2 (10 Volt - used with 'V')

The apparatus is designed to operate from a DC supply of up to 35V on terminals 7 to 12, 14 and 15, and power rail connector terminals 1 and 2. The segregation of the hazardous area circuits meets the requirements for 250V.

Electrical Ratings/Parameters

Type KFD2-STC(V)4-Ex1. and Type KFD2-STC(V)4-Ex1.2O

For terminals 7 to 12, 14 and 15, and power rail terminals 1 & 2:

Um = 250V

For Terminals 1 and 3:

Uo = 25.4 V Io = 86.8 mA Po = 551 mW Ci = 12 nF Li = 0

The capacitance and either the inductance or the inductance to resistance ratio (L/R) of the hazardous area load must not exceed the following values:

Group	Capacitance (µF)	Inductance (mH)	L/R Ratio (µH/Ω)
I	4.3	29	833

For Terminals 3 and 2 (& 5):

Uo = 3.5 V Io = 74 mA Po = 64 mW Ui = 30 V Ii = 115 mA Ci = 0 Li = 0

This certificate and schedule may only be reproduced in full

Certificate of Conformity
Ex EQUIPMENT

Certificate No.:	ANZEx 13.2004X	Current Issue: 3	Date of Issue: 2026-06-08

The capacitance and either the inductance or the inductance to resistance ratio (L/R) of the hazardous area load must not exceed the following values:

Group	Capacitance (µF)	Inductance (mH)	L/R Ratio (µH/Ω)
I	1000	42	7207

For Terminals 1, 2 (& 5) and 3:

Uo = 25.4 V Io = 115 mA Po = 0.584 W Ci = 12 nF Li = 0

The capacitance and either the inductance or the inductance to resistance ratio (L/R) of the hazardous area load must not exceed the following values:

Group	Capacitance (µF)	Inductance (mH)	L/R Ratio (µH/Ω)
I	4.3	17	639

For Terminals 6 and 5 (&2):

Uo = 8.7 V Io = 0 Co = 5.9 µF Ui = 30 V Ii = 115 mA Ci = 0 Li = 0

Type KFD2-STC4-Ex1.H and Type KFD2-STC4-Ex1.2O.H

For terminals 7 to 12, 14 and 15, and power rail terminals 1 & 2:

Um = 250 V

For Terminals 1 and 3:

Uo = 27.2 V Io = 93 mA Po = 0.632 W Ci = 12 nF Li = 0

The capacitance and either the inductance or the inductance to resistance ratio (L/R) of the hazardous area load must not exceed the following values:

Group	Capacitance (µF)	Inductance (mH)	L/R Ratio (µH/Ω)
I	4.0	51.9	687

For Terminals 3 and 2 (& 5):

Uo = 3.5 V Io = 73 mA Po = 64 mW Ui = 30 V Ii = 117 mA Ci = 0 Li = 0

The capacitance and either the inductance or the inductance to resistance ratio (L/R) of the hazardous area load must not exceed the following values:

Group	Capacitance (µF)	Inductance (mH)	L/R Ratio (µH/Ω)
I	1000	42	7207

For Terminals 1, 2 (& 5) and 3:

Uo = 27.2 V Io = 117 mA Po = 0.639 W Ci = 12 nF Li = 0

This certificate and schedule may only be reproduced in full
Simtars

Certificate of Conformity
Ex EQUIPMENT

Certificate No.: **ANZEx 13.2004X**	*Current Issue:* 3	*Date of Issue:* 2026-06-08

The capacitance and either the inductance or the inductance to resistance ratio (L/R) of the hazardous area load must not exceed the following values:

Group	Capacitance (µF)	Inductance (mH)	L/R Ratio (µH/Ω)
I	4.0	30	409

For Terminals 6 and 5 (&2):

Uo = 8.7V Io = 0 Co = 5.9µF Ui = 30V Ii = 117mA Ci = 0 Li = 0

The above load parameters apply when one of the two conditions below is given:

- the total Li of the external circuit (excluding the cable) is < 1% of the Lo value or
- the total Ci of the external circuit (excluding the cable) is < 1% of the Co value.

The above parameters are reduced to 50% when both of the two conditions below are given:

- the total Li of the external circuit (excluding the cable) is ≥ 1% of the Lo value and
- the total Ci of the external circuit (excluding the cable) is ≥ 1% of the Co value.

Routine testing of the transformer shall be carried out in accordance with clause 11.2 of IEC 60079-11: 2006.

Specific Conditions of Use:

1. The safety device must be installed in a controlled environment with suitably reduced pollution.

Conditions of Certification:

None

This certificate and schedule may only be reproduced in full
Simtars

Certificate of Conformity
Ex EQUIPMENT

Certificate No.: **ANZEx 13.2004X**	*Current Issue:* 3	*Date of Issue:* 2026-06-08

Manufacturer's Documents/Drawings associated with this issue:

Document/Drawing Title	Document/Drawing Number	Pages / Sheets	Revision	Date
GB/BAS/ExTR14.0292/00				
Summary KFD2-CR4-Ex1(.2O).. & KFD2-STC(V)4-Ex1(.2O)..	266-015IE-F	1	-	2014-May-12
Mechanical parts Moulded Transformer Housing - base	266-010BS-04E (Sheet 1 of 15)	1	-	2014-Mar-27
Mechanical parts Moulded Transformer Housing – alternative base	266-010BS-04E (Sheet 2 of 15)	1	-	2014-Mar-27
Mechanical parts Moulded Transformer Housing – cover	266-010BS-04E (Sheet 3 of 15)	1	-	2014-Mar-27
Mechanical parts Transformer – Toroidal Housing	266-010BS-04E (Sheet 4 and 5 of 15)	2	-	2014-Mar-27
Mechanical parts KF – Housing 15 Term. Asymm	266-010BS-04E (Sheet 6 to 15 of 15)	10	-	2014-Mar-27
Type Label KFD2-STC(V)4-Ex1(.2O)..	266-014BS-10T	3	-	2014-May-12
GB/BAS/ExTR15.0306/00				
Summary KFD2-CR4-Ex1(.2O).. & KFD2-STC(V)4-Ex1(.2O)..	266-015IE-G	1	-	2015-Oct-15
Components KFD2-STC(V)4-Ex1(.2O).. & KFD2-STC(V)4-Ex1(.2O)(.H)..	266-014BS-02U	9	-	2015-Oct-15
GB/BAS/ExTR16.0291/00				
Summary KFD2-CR4-Ex1(.2O).. & KFD2-STC(V)4-Ex1(.2O)(,H)..	266-014BS-V	1	-	2016-Sep-15
Schematic KFD2-CR4-Ex1(.2O).. & KFD2-STC(V)4-Ex1(.2O)..	266-014BS-01V	4	-	2015-Dec-10
Safety Relevant Components KFD2-CR4-Ex1(.2O).. & KFD2-STC(V)4-Ex1(.2O)(.H)..	266-014BS-02V	2	-	2016-Sep-15
Assembly -top KFD2-CR4-Ex1(.2O).. & KFD2-STC(V)4-Ex1(.2O)..	266-014BS-03V (Sheet 1 of 2)	1	-	2016-Mar-23
Assembly -bottom KFD2-CR4-Ex1(.2O).. & KFD2-STC(V)4-Ex1(.2O)..	266-014BS-03V (Sheet 2 of 2)	1	-	2016-Mar-23
Mechanical parts Moulded Transformer Housing - base	266-010BS-04F (Sheet 1 of 15)	1	-	2016-Mar-23
Mechanical parts Moulded Transformer Housing – alternative base	266-010BS-04F (Sheet 2 of 15)	1	-	2016-Mar-23

This certificate and schedule may only be reproduced in full
Simtars

Certificate of Conformity
Ex EQUIPMENT

Certificate No.: **ANZEx 13.2004X**	*Current Issue:* 3	*Date of Issue:* 2026-06-08

Document/Drawing Title	Document/Drawing Number	Pages / Sheets	Revision	Date
Mechanical parts Moulded Transformer Housing – cover	266-010BS-04F (Sheet 3 of 15)	1	-	2016-Mar-23
Mechanical parts Transformer – Toroidal Housing	266-010BS-04F (Sheets 4 and 5 of 15)	2	-	2016-Mar-23
Mechanical parts KF – Housing 15 Term. Asymm	266-010BS-04F (Sheets 6 to 15 of 15)	10	-	2016-Mar-23
Main Printed Circuit Board KFD2-CR4-Ex1(.2O)... & KFD2-STC(V)4-Ex1(.2O)(.H)…	266-014BS-05V (Sheets 1 to 5 of 6)	5	-	2016-Mar-23
Zener diode 4-way array PCB KFD2-CR4-Ex1(.2O)… & KFD2-STC(V)4-Ex1(.2O)(.H)…	266-014BS-05V (Sheet 6 of 6)	1	-	2016-Mar-23
Transformer details for T101 & T201 KFD2-CR4-Ex1(.2O)… & KFD2-STC(V)4-Ex1(.2O)…	266-014BS-06V (Sheets 1 and 2 of 6)	2	-	2016-Sep-15
Transformer details for T102 & T202 KFD2-CR4-Ex1(.2O)... & KFD2-STC(V)4-Ex1(.2O)…	266-014BS-06V (Sheets 3 and 4 of 6)	2	-	2016-Sep-15
Transformer details for T102 KFD2-CR4-Ex1 & KFD2-STC(V)4-Ex1	266-014BS-06V (Sheets 5 and 6 of 6)	2	-	2016-Sep-15
Labels				
Type Label KFD2-STC(V)4-Ex1(.2)(.H)...	266-0014SI-10A	1	-	2022-Sep-02

Note: An * is included before the title of documents that are new or revised.

Additional Information:

None

JAS-ANZ
WWW.JAS-ANZ.ORG/REGISTER

This certificate and schedule may only be reproduced in full

Simtars

Certificate of Conformity
Ex EQUIPMENT

Certificate No.: **ANZEx 13.2004X**	*Current Issue:* 3	*Date of Issue:* 2026-06-08

Register of Issues and Variations
includes the current issue

Issue 0 dated 2013-02-25

Standards relevant for this issue:

IEC 60079-0:2007 Ed 5.0	Explosive atmospheres Part 0: Equipment—General requirements
IEC 60079-11:2006 Ed 5.0	Explosive atmospheres Part 11: Equipment protection by intrinsic safety "i"

Test & Assessment Reports relevant for this issue:

TR No. & Issuing CBs:	UK/BAS/03/1051, UK/BAS/04/0566, GB/BAS/ExTR06.0084/00, GB/BAS/ExTR08.0046/00, GB/BAS/ExTR10.0301/00; Baseefa NI13/0002; Simtars
QAR No. & Issuing CB:	DE/PTB/QAR06.0007/03, DE/PTB/QAR06.0008/05; PTB
File Reference:	12/0126

Issue 1 dated 2022-09-15

Standards relevant for this issue:

IEC 60079-0: 2011 Ed 6.0	Explosive atmospheres Part 0: Equipment – General requirements
IEC 60079-11: 2011 Ed 6.0	Explosive atmospheres Part 11: Equipment protection by intrinsic safety “i”

Variations Permitted by this Issue

- Update editions of the standards
- Changes to the transformer
- Use of an alternative fuse
- Addition of an ‘X’ suffix to the certificate number for the condition “The safety device must be installed in a controlled environment with suitably reduced pollution” due to the removal of the conformal coating
- Modification of Applicant and Manufacturer names to show current legal form

Test & Assessment Reports relevant for this issue:

TR No. & Issuing CBs:	GB/BAS/ExTR14.0292/00, GB/BAS/ExTR15.0306/00, GB/BAS/ExTR16.0291/00; BASEEFA
QAR No. & Issuing CB:	DE/PTB/QAR06.0008/16 - PTB
File Reference:	060041Audit

This certificate and schedule may only be reproduced in full

Certificate of Conformity
Ex EQUIPMENT

Certificate No.: **ANZEx 13.2004X**	*Current Issue:* 3	*Date of Issue:* 2026-06-08

Issue 2 dated 2025-06-04

Standards relevant for this issue:

IEC 60079-0: 2011 Ed 6.0 Explosive atmospheres Part 0: Equipment – General requirements

IEC 60079-11: 2011 Ed 6.0 Explosive atmospheres Part 11: Equipment protection by intrinsic safety "i"

Variations Permitted by this Issue

- Corrected the Lo value for terminals 3 and 2 (&5) in issue 1 from from 421 mH to 42 mH
- Addition of Vietnam as a manufacturing location

Test & Assessment Reports relevant for this issue:

TR No. & Issuing CBs:	GB/BAS/ExTR14.0292/00, GB/BAS/ExTR15.0306/00, GB/BAS/ExTR16.0291/00; BASEEFA
QAR No. & Issuing CB:	DE/PTB/QAR06.0008/21; PTB
File Reference:	060041Audit

Issue 3 dated 2026-06-08

Standards relevant for this issue:

IEC 60079-0: 2011 Ed 6.0 Explosive atmospheres Part 0: Equipment – General requirements

IEC 60079-11: 2011 Ed 6.0 Explosive atmospheres Part 11: Equipment protection by intrinsic safety "i"

Variations Permitted by this Issue

- Update address for manufacturing location Vietnam
- Change auditing CB and linked QAR

Test & Assessment Reports relevant for this issue:

TR No. & Issuing CBs:	GB/BAS/ExTR14.0292/00, GB/BAS/ExTR15.0306/00, GB/BAS/ExTR16.0291/00; BASEEFA
QAR No. & Issuing CB:	HR/FIDI/QAR24.0001/03; Fiditas
File Reference:	060041Audit

This certificate and schedule may only be reproduced in full