

Radar motion sensor ECHO-D white narrow



- Standard radar motion sensor
- Detection of people and objects for automatic doors
- Bidirectional sensing and adjustment of detection field
- Remote control or push button for functionality setting
- Wall and ceiling mountable

Standard radar motion sensor with basic functionality, detection range 4 m x 2 m, max. installation height 4 m, white housing, solid-state relay, cable connection




Function


This device is a radar motion sensor with basic functionality. The functionality is based on the 24 GHz radar technology The basic functionality which can be activated includes among others direction detection, cross-traffic suppression, and immunity. The sensor is integrated in a simple and well-designed housing. The opening impulse sensor is easy to mount and to commission. The built-in antenna enables bidirectional sensing. This version has a narrow detection area.


Application

- Opening impulse sensors for automatic doors and industrial doors
- Monitoring approach areas to elevators
- Motion sensors for people and objects
- · Impulse sensors for escalators

Dimensions








Technical Data

General specifications			
Sensing range		$4000x2000$ mm (DxW) at 2200 mm mounting height and 30° inclination angle	
Function principle			
Detection speed		min. 0.05 m/s	
Setting angle			
Rotation angle		-40 40 ° in 5 ° increments	
Inclination angle		0 90 $^{\circ}$ in 5 $^{\circ}$ increments	
Operating frequency		24.15 24.25 GHz K-Band	
Operating mode		Radar motion sensor	
Transmitter radiated power (EIRP)		< 20 dBm	
Functional safety related parameters			
MTTF _d		696 a	
Mission Time (T _M)		20 a	
Diagnostic Coverage (DC)		0 %	
Indicators/operating means			
Function indicator		detection: LED green push button indication: LED yellow / green	
Control elements		Push button for selection of operating modes: sensitivity, direction detection, cross-traffic suppression, slow-motion mode, relay switching type, hold time, immunity	
Electrical specifications			
Operating voltage	U _B	12 24 V DC \pm 10 %	
No-load supply current	I_0	≤ 55 mA at 24 V DC	
Power consumption	P ₀	≤ 1.32 W	

Technical Data

Output	
Switching type	Normally open/closed (NO/NC)
Signal output	solid-state relay
Switching voltage	max. 28 V AC / 36 V DC
Switching current	max. 0.1 A AC / 0.1 A DC
Hold time	1.5 s / 3 s
Approvals and certificates	
CE conformity	2014/53/EU This device can be used in all countries within the European Union. In other countries, all applicable national regulations must be observed.
CCC approval	CCC approval / marking not required for products rated ≤36 V
Ambient conditions	
Operating temperature	-20 55 °C (-4 131 °F)
Storage temperature	-30 70 °C (-22 158 °F)
Relative humidity	max. 90 % non-condensing
Mechanical specifications	
Mounting height	max. 4 m
Degree of protection	IP54
Connection	Connecting cable 2.5 m included with delivery
Material	
Housing	PC (Polycarbonate)
Mass	approx. 70 g
Dimensions	75 mm x 64 mm x 50 mm
Height	64 mm
Width	75 mm
Depth	50 mm

Connection



1	Push button.	left: -

- 2 Push button and detection indication: LED green
- 3 Push button indication: LED yellow
- 4 Push button, right: +
- 5 Antenna

6	Connector

- 7 Detection: LED green
- 8 Rotation angle
- 9 Side cable entry (optional)
- 10 Cable entry (default)

Function Principle

Microwave sensors are microwave scanners that use the principle of the Doppler radar. The most important requirement for microwave detection is that the object to be detected is moving. Some applications include controlling automatic doors and industrial doors.

The microwave sensors emit microwaves of a defined frequency to detect people and large objects moving at speeds between 0.05 m/s ... 2 m/s. Stationary people or objects are not detected.

Based on the latest 24 GHz technology with integrated microprocessor control, these sensors provide a high level of reliability, even in difficult operational conditions. The 24 GHz frequency, known as 'K-band,' is reserved by CETECOM for this application area all round the world.