

Pinout Table

Termination board field side			Modules		Termination board control side
Module	Channel	IS terminal TB1	IS terminals SL2 field side	Non-IS terminals SL1 control side	System connector X1
1	1	1	5a	8a	A9
		2	5b		
		3	1a	7a	B9
		4	1b		
2	2	5	5a	8a	A8
		6	5b		
		7	1a	7a	B8
		8	1b		
3	3	9	5a	8a	A7
		10	5b		
		11	1a	7a	B7
		12	1b		
4	4	13	5a	8a	A6
		14	5b		
		15	1a	7a	B6
		16	1b		
5	5	17	5a	8a	A5
		18	5b		
		19	1a	7a	B5
		20	1b		
6	6	21	5a	8a	A4
		22	5b		
		23	1a	7a	B4
		24	1b		
7	7	25	5a	8a	A3
		26	5b		
		27	1a	7a	B3
		28	1b		
8	8	29	5a	8a	A2
		30	5b		
		31	1a	7a	B2
		32	1b		



The typical circuit drawing has to be observed. For information see corresponding data sheet on www.pepperl-fuchs.com.