

Pepperl+Fuchs SE  
 Lilienthalstrasse 200  
 68307 Mannheim  
 Germany  
 Phone +49 621 776-0  
 Fax +49 621 776-1000

No: DOC-5126A  
 Date: 2023-09-14

Copyright Pepperl+Fuchs  
[www.pepperl-fuchs.com](http://www.pepperl-fuchs.com)



**Affixed UKCA Marking**



**Signatures**

Mannheim, 2023-09-14

i.V. Rolf Wessels  
 Executive Vice President Business  
 Unit MCC+HMI

i.V. Jörg Hartleb  
 COO ECOM Instruments GmbH

**Declaration of conformity**

We, Pepperl+Fuchs SE declare under our sole responsibility that the **products** listed below are in conformity with the listed **UK Regulations** as indicated below and amended by **UK SI 2019 No. 696**, and **standards**.

**Product family**

Product family	Description
PAD-EX01P8DZ2 [x1][x2][x3][x4][x5][x6][x7]	Intrinsically Safe Tablet PC

The [X] marked letters of the type code are placeholders and can be replaced by the code described in ANNEX TYPE CODE.

**Regulations and Standards**

UK Regulation	Standards
UK SI 2012 No. 3032 (RoHS)	EN IEC 63000:2018-12
UK SI 2016 No. 1107 (EX)	EN 60079-11:2012-01 EN IEC 60079-0:2018-07
UK SI 2017 No. 1206 (RE)	EN 300328 V 2.2.2:2019-07 EN 300440 V 2.1.1:2017-03 EN 301489-1 V 2.2.3:2019-11 EN 301489-17 V 3.2.4:2020-09 EN 301489-19 V 2.2.1:2022-09 EN 301489-52 V 1.1.0:2016-11 EN 301893 V 2.1.1:2017-05 EN 301908-1 V 15.1.1:2021-09 EN 303413 V 1.2.1:2021-04 EN 50566:2017-10 EN 62479:2010-09 EN IEC 62368-1:2020-03 EN IEC/IEEE 62209-1528:2021-11

**ANNEX UK SI 2016 No. 1107 (EX)**

**Marking and Certificates**

Marking	Certificate	ID
Ex II 3 D Ex II 3 G	EPS 16 ATEX 1 163 X	EPS

**Key for ID**

ID	Responsible Body
EPS	Bureau Veritas Consumer Products Services Germany GmbH Wilhelm-Hennemann-Straße 8 19061 Schwerin Germany

## ■ ANNEX TYPE CODE

The [X] marked letters of the type code are placeholders and can be replaced by the following code:

PAD-EX01P8DZ2[x1][x2][x3][x4][x5][x6][x7]			
Variable	Feature	Option	Description
x1	Region / Country	[EUR] [EAC] [BRA] [xxx]	Europe Russia / EAC Brazil Country specific variant acc. to Alpha-3 code (ISO alpha-3)
x2	Camera	[C] [N]	With Camera Without Camera
x3	Processor	[05] [07]	i5 processor i7 processor
x4	Storage RAM	[08] [16]	8G RAM 16 GB RAM
x5	Storage SSD	[128] [256] [512]	128 GB SSD 256 GB SSD 512 GB SSD
x6	Scanner / LTE	[W2D] [LTE] [L2D] [WIF]	2D Scanner + WiFi LTE Module LTE Module + 2D Scanner Only WiFi
x7	Customized	[000] [HAM]	Standard ECOM HART-Modem (Viator)-KIT