

## Pinout Table

Termination board field side			Modules		Termination board control side	
Module	Channel	IS terminals M1 ... M16	IS terminals SL2 field side	Non-IS terminals SL1 control side	System connector X1	Signal name FBM207b
1	1	1	5a	8a	36	i01+
		4	5b			
		2	1a	7a	18	i01S
		5	1b			
2	2	1	5a	8a	35	i02+
		4	5b			
		2	1a	7a	17	i02S
		5	1b			
3	3	1	5a	8a	34	i03+
		4	5b			
		2	1a	7a	16	i03S
		5	1b			
4	4	1	5a	8a	33	i04+
		4	5b			
		2	1a	7a	15	i04S
		5	1b			
5	5	1	5a	8a	32	i05+
		4	5b			
		2	1a	7a	14	i05S
		5	1b			
6	6	1	5a	8a	31	i06+
		4	5b			
		2	1a	7a	13	i06S
		5	1b			
7	7	1	5a	8a	30	i07+
		4	5b			
		2	1a	7a	12	i07S
		5	1b			
8	8	1	5a	8a	29	i08+
		4	5b			
		2	1a	7a	11	i08S
		5	1b			
9	9	1	5a	8a	28	i09+
		4	5b			
		2	1a	7a	10	i09S
		5	1b			
10	10	1	5a	8a	27	i10+
		4	5b			
		2	1a	7a	9	i10S
		5	1b			
11	11	1	5a	8a	26	i11+
		4	5b			
		2	1a	7a	8	i11S
		5	1b			
12	12	1	5a	8a	25	i12+
		4	5b			
		2	1a	7a	7	i12S
		5	1b			
13	13	1	5a	8a	24	i13+
		4	5b			
		2	1a	7a	6	i13S
		5	1b			
14	14	1	5a	8a	23	i14+
		4	5b			
		2	1a	7a	5	i14S
		5	1b			

DOCT-6984 70123791 2020-09

Refer to "General Notes Relating to Pepperl+Fuchs Product Information".

Pepperl+Fuchs Group  
www.pepperl-fuchs.comUSA: +1 330 486 0002  
pa-info@us.pepperl-fuchs.comGermany: +49 621 776 2222  
pa-info@de.pepperl-fuchs.comSingapore: +65 6779 9091  
pa-info@sg.pepperl-fuchs.com

**PEPPERL+FUCHS**

## Pinout Table

Termination board field side			Modules		Termination board control side	
Module	Channel	IS terminals M1 ... M16	IS terminals SL2 field side	Non-IS terminals SL1 control side	System connector X1	Signal name FBM207b
15	15	1	5a	8a	22	i15+
		4	5b			
		2	1a	7a	4	i15S
		5	1b			
16	16	1	5a	8a	21	i16+
		4	5b			
		2	1a	7a	3	i16S
		5	1b			
					1, 2, 19, 20, 37	n.c.

Terminal pinout	Connector	Pin	Signal name
Power supply	X20	6	Supply I -
		5	Supply I +
	X20	4	Supply II -
		3	Supply II +
Volt-free fault indication output	X20	1, 2	Fault

Module pinout (SL1): module 1 ... 16	
V <sub>cc</sub>	2a (+)
	2b (+)
GND	1a (-)
	1b (-)
Fault	6b



The loop drawing has to be observed. For information see corresponding data sheet on [www.pepperl-fuchs.com](http://www.pepperl-fuchs.com).