



# Docking station

## IQZ-HH27-CHARGER1

Docking station for IQT1-HH27 and IPT-HH27



### Function

The docking station QZ-HH27-CHARGER1 enables you to connect the IQT1-HH27 and IPT-HH27 handhelds to a PC via USB or Ethernet. The docking station is also able to charge the handhelds when a battery is inserted.

### Technical Data

#### Indicators/operating means

LED red/green	Power: green/off Charge: green/red Connect: green/off
---------------	---

#### Input

Input voltage	100 V AC ... 240 V AC 47 ... 63 Hz
Input current	max. 1 A

#### Output

Output rated operating current	2.6 A
Output voltage	15 V DC

#### Approvals and certificates

CE conformity	CE
---------------	----

#### Ambient conditions

Ambient temperature	0 ... 45 °C (32 ... 113 °F)
Storage temperature	-20 ... 70 °C (-4 ... 158 °F)

#### Mechanical specifications

Connection	USB (type A and B) and LAN (RJ45)
Mass	785 g
Dimensions	122 mm x 125 mm x 127 mm
Note	No option to charge a spare battery available Power supply (EU, US) and USB cable included in the scope of delivery

### Matching system components

	<b>IPT-HH27</b>	Handheld (125 kHz)
	<b>IQT1-HH27</b>	Handheld (13.56 MHz)

Release date: 2020-03-27 Date of issue: 2020-03-27 Filename: 293813\_eng.pdf

Refer to "General Notes Relating to Pepperl+Fuchs Product Information".

Pepperl+Fuchs Group  
www.pepperl-fuchs.com

USA: +1 330 486 0001  
fa-info@us.pepperl-fuchs.com

Germany: +49 621 776 1111  
fa-info@de.pepperl-fuchs.com

Singapore: +65 6779 9091  
fa-info@sg.pepperl-fuchs.com

 **PEPPERL+FUCHS**