







# **Model Number**

SJ2-SN-Y38287

### **Features**

2 mm slot width

# **Application**



## Danger!

In safety-related applications the sensor must be operated with a qualified fail safe interface from

Pepperl+Fuchs, such as KFD2-SH-EX1. Consider the "exida Functional Safety Assessment" document which is available on www.pepperl-fuchs.com as an integral part of this product's documentation.

### **Technical Data**

# General specifications

Switching element function NAMUR, NC Slot width 2 mm Depth of immersion (lateral) 5 ... 7 typ. 6 mm Installation
Output polarity

**Nominal ratings** 

Nominal voltage 8 V 5 ... 25 V 0 ... 5000 Hz Operating voltage Switching frequency

Current consumption

Measuring plate not detected  $\geq$  3 mA Measuring plate detected ≤ 1 mA

**Ambient conditions** 

Ambient temperature -40 ... 100 °C (-40 ... 212 °F)

Safety Function

**Mechanical specifications** 

Connection type flexible leads LIFYW, 105 mm Core cross-section 0.06 mm<sup>2</sup>

Housing material Degree of protection PBT IP67

Note adjustable stop General information

Use in the hazardous area see instruction manuals


Category Compliance with standards and directives

Standard conformity NAMUR EN 60947-5-6:2000 IEC 60947-5-6:1999 EN 60947-5-2:2007 Standards


Approvals and certificates

**UL** approval cULus Listed, General Purpose cCSAus Listed, General Purpose CSA approval


# **Dimensions**



IEC 60947-5-2:2007



# **Electrical Connection**



#### ATEX 2G

Instruction

### Device category 2G

EC-Type Examination Certificate CE marking

ATEX marking Directive conformity

Standards

Appropriate type

Effective internal capacitance Ci Effective internal inductance Li

General

Ambient temperature

Installation, Comissioning

Maintenance

## Specific conditions

Protection from mechanical danger

#### Manual electrical apparatus for hazardous areas

for use in hazardous areas with gas, vapour and mist PTB 00 ATEX 2049 X €0102

⟨ II 2G Ex ia IIC T6 Gb

94/9/EG

EN 60079-0:2009, EN 60079-11:2012 Ignition protection "Intrinsic safety"
Use is restricted to the following stated conditions

 $\leq$  30 nF; a cable length of 10 m is considered.

 $\leq$  100  $\mu$ H; a cable length of 10 m is considered.

The apparatus has to be operated according to the appropriate data in the data sheet and in this instruction manual. The EC-Type Examination Certificate has to be observed. The special conditions must be adhered to!

The temperature ranges, according to temperature class, are given in the EC-Type Examination Certificate.

Laws and/or regulations and standards governing the use or intended usage goal must be observed. The intrinsic safety is only assured in connection with an appropriate related apparatus and according to the proof of intrinsic safety.

No changes can be made to apparatus, which are operated in hazardous areas. Repairs to these apparatus are not possible.

When used in the temperature range below -20 °C the sensor should be protected from knocks by the provision of an additional housing.

PEPPERL+FUCHS